

MICRO SERIES PRODUCT SPECS



PRODUCT NAME _____ Guardian Angel™ Micro™ Series LED Light Bar

LIGHT SOURCE _____ 14 LEDs

COLORS _____ Red, White, Yellow, Green, Orange, Infrared

BRIGHTNESS _____ Up to 500 lumen total output (varies by brightness setting and LED color). 3+ Miles Visibility

SIZE _____ 2" Wide x 1.75" Long x 0.875" High

WEIGHT _____ 64.4grams, 2.27oz

BATTERY _____ Type: Rechargeable Lithium Ion Polymer Battery
Capacity: 700 mAh

Charging Time: Approximately 1 hour 30 mins

Normal Voltage: 3.7V

Certification: UN38.3c IEC62133, CE, RoHS Compliant

Battery Life hr/charge: Varies based on Brightness Setting (Max, High, Medium, Low) and flash pattern. Min 1 hour, Max 90 hours, most commonly used modes 12-24 hours.

Battery Life Cycle: Minimum 3,000 charging cycles

CHARGING _____ Connector: USB Type-C

Input: AC 100-240V - 50/60Hz. 0.6A

Output: 5.0V - 1000mA

CASING _____ Material: Proprietary Polycarbonate, ABS Rubber
IP Rating: IP68

Depth Tested: 8.2 Feet / 2.5 Meters

Material Flammability Rating: UL 746B, UL94

MOUNTING _____ Neodymium Rare Earth Magnet

ENVIRONMENT _____ Operational Temp: -40F°-230°F / -40C°-110C°

Storage Temp: 68-82°F / 20-28°C

GA EMERGENCY MODE

- 1st Press= All LEDs Flashing
- 2nd Press= OFF
- Hold= Scrolling Sequence (Push Again to Turn Off)

TETHER ATTACHMENT

Tether Accessory Attachment

BRIGHTNESS SETTINGS

Max, High, Medium, Low or SOS Light Pattern

TOP LED

Enhanced Spotlight Lens with Dedicated Button

- 1st Press= Constant On
- 2nd Press= Constant Flash
- 3rd Press= OFF

DURABLE

Waterproof,
Dustproof,
Shockproof,
IP68 Rated

CHARGING PORT

Rechargeable
Type-C USB
Charging Port

REAR LED'S

- 1st Press= Constant On
- 2nd Press= Constant Blinking
- 3rd Press= Scrolling Sequence
- 4th Press= OFF
- Hold= Battery Level Indicator

WORK LIGHT

- 1st Press= Single LED On
- 2nd Press= OFF
- Hold= Standard Operating Mode (All Front LED's On, Rear LED's Flashing)

BUILT IN MAGNET

Super Strong Built-in Rare Earth Magnet Mounting System (on underside)

FRONT LED'S

- 1st Press= Constant On
- 2nd Press= Constant Blinking
- 3rd Press= Scrolling Sequence
- 4th Press= OFF
- Hold On/Off = All Front LED'S





GUARDIAN ANGEL

QUICK START GUIDE

Get Going with Your Guardian Angel

TOP FOCUSED LED

- (1) ON
- (2) FLASHING
- (3) OFF


TETHER ATTACHMENT

EMERGENCY MODE

- (1) FRONT & REAR *FLASHING*
- (2) OFF
- (3) HOLD: ALL LEDs *FLASHING*
- (4) DOUBLE PRESS: TURNS OFF ALL LEDs



HOW-TO VIDEOS



REAR LEDs

- (1) CONSTANT ON
- (2) CONSTANT *FLASHING*
- (3) SCROLLING SEQUENCE MOVES LEFT TO RIGHT - FRONT VIEW
- (4) OFF
- HOLD: BATTERY LEVEL INDICATOR

FULL ■■■■■■
HALF ■■■■
LOW ■

WORK LIGHT

- (1) RED LED ON
- (2) RED LEDs ON
- (3) WHITE LEDs ON/RED OFF
- (4) OFF
- HOLD: STANDARD OPERATING MODE

BRIGHTNESS SETTINGS

- (1) MAX
- (2) HIGH
- (3) MEDIUM
- (4) LOW
- HOLD: ON/OFF FOR SOS SIGNALING

FRONT LEDs

- (1) CONSTANT ON
- (2) CONSTANT *FLASHING*
- (3) SCROLLING SEQUENCE MOVES LEFT TO RIGHT - FRONT VIEW
- (4) OFF

ACTIVATE YOUR DEVICE



INITIAL USE: Hold down the front & rear buttons for 2 seconds. The white work light will turn on to signal it's activated. Device will turn on at max brightness.




MAX.
High
Med.
Low

BRIGHTNESS SETTINGS: Push the brightness button until desired setting is reached.

Low/Medium are ideal for most low-light situations.

High/Max are optimal for day-time use. Battery life is shorter on these settings.



POWERING DOWN: Hold down the front & rear buttons for 3 seconds to turn it off. The white work light will flash 3 times.

PRO TIPS



PRESS AND HOLD the small button on the front of the device to activate standard mode. This is the most popular mode, which turns on the white front light and rear flashing lights.



EMERGENCY MODE:

The big GA button in the middle will activate flashing front and rear lights. Press again to turn it off.



QUICK OFF:

Double press the big GA button to turn off all LEDs from any mode.

ONE LIGHT, DOZENS OF MOUNTS, 1,000s OF USES

Each mount features a built-in rare-Earth magnet (the strongest around) that securely attaches to any Guardian Angel light.

MULTI-PURPOSE MOUNTS



Universal Clip Mount
ACC-UCM

Best For: Hats, Belts, Bags, Outer Carrier, Molle Webbing, Radio Strap & Backpacks



Small Universal Clip Mount
ACC-UCMS

Best For: Hat Brims, Thin Straps



Jaw Clip Mount
ACC-JCM

Best For: Quick Detaching, Shirt, Jacket, Backpack, & Safety Vest



Clamp-On Strap Mount
ACC-COSM

Best For: Radio Straps, & Straps Up To 1.5" Width



Snap-Lock Mount
ACC-SLM

Best For: Dog Collars, Leashes & Harnesses



Strap & Epaulet Mount
ACC-SCM

Best For: Uniform Epaulets



Arm Strap Mount
ACC-MSML

Best For: Walking & Running



Velcro Clip Mount
ACC-MVCM

Best For: Any Velcro Surface



Stabilizer Clip Mount
ACC-STCM

Best For: Shoulder Mounting

VEHICLE, EQUIPMENT & GEAR MOUNTS



Cone Mount
ACC-MCM

Best For: Traffic & Safety Cones



Action Mount
ACC-AM

Best For: GoPro Action Camera Mounts



Bike/Rail Rubber Strap Mount
ACC-RBM

Best For: Handlebars & Rails




Bike/Rail Strap Mount
ACC-BSM

Best For: Handlebars, Seat Posts, & Bars 0.5"-1.75" Diameter



Velcro Strap Mount
ACC-MVSM

Best For: Rails, Posts & Vented Bike Helmets



Non-metallic Surface Adhesive & Screw Mount
ACC-NMSM

Best For: Any Non-Metallic Surface



Picatinny Rail Mount
ACC-MPRM

Best For: Picatinny Rails (Commonly Found On Firearms)



Marine Mount Bundle
GRP-M-M-1

Best For: Kayaks, Paddle Sports, Boats, PFDs

HELMET MOUNTS



Hard Hat Earmuff Mount
ACC-HHEM

Best For: Hard Hats With Earmuff Slots, & Type 2 Safety Helmets



Hard Hat Mount
ACC-HHM

Best For: Hard Hats With Multiple Mounting Locations, & Type I Hard Hats Only



Aluminum Fire Helmet Mount
ACC-FHA

Best For: Traditional Fire Helmet Brims



Euro Fire Helmet Mount
ACC-FHM

Best For: Euro-Style Helmets



Helmet Strap With 2 Mounts
ACC-HHMS

Best For: Mounting 2 Lights To Helmet



Helmet Rail Mount
ACC-MHRM

Best For: Tactical Helmets With Mounting Rails