

FC PASSED (UL) CE (ROHS)

# ELITE SERIES PRODUCT SPECS:

**PRODUCT NAME** → Guardian Angel<sup>™</sup> Elite<sup>™</sup> Series LED Light Bar

LIGHT SOURCE — 18 LED'S

Red, White, Blue, Yellow, Green, Orange, Infrared

BRIGHTNESS — Up to 800 lumens (varies by model),

5+ Miles Visibility

**SIZE** 2.75"W x 1.87" L x 1.0" H

**WEIGHT** — 3.25oz, 92.4g

**BATTERY** Type: Rechargeable Lithium Polymer Battery

Capacity: 1400mAh / 5.18Wh Charging Time: Approx. 1.5 hrs

Normal Voltage: 3.7V

Certification: UN38.3, IEC62133, CE, RoHS Compliant

Battery Life hr/charge: Varies based on

brightness setting & light mode. 1.5 – 150 hours

Battery Life Cycle: 3,000-5,000 cycles

**CHARGING** — Connector: Type C USB

Input: AC 100-240V - 50/60Hz. 0.6A

Output: 5.0V - 2000mA

CASING — Material: Polycarbonate Lens, Glass Filled

Polycarbonate Exterior Covers and USB Door, High Tempatere Rubber Buttons & Water Seals

IP Rating: IP68 Water/Dust Proof Rating Flammability Rating: UL 746B, UL94

MOUNTING — Neodymium iron boron Grade NB42 magnets

ENVIRONMENT — Operational Temp & Humidity: -40C°- 110C°
Storage Temp & Humidity: 20-28C°

**GA EMERGENCY MODE** 

- · 1st Press= All LEDs Flashing
- · 2nd Press= OFF
- · Hold= Scrolling Sequence

Battery Level

Hold

(Push Again to Turn Off)

TETHER ATTACHMENT

**Tether Accessory Attachment** 

ANGEL

Front/Rear

Hold

MAX.

High

Med.

Low

Front

# **TOP LED**

Enhanced Spotlight Lens with Dedicated Button

- · 1st Press= Constant On
- · 2nd Press= Constant Flash
- · 3rd Press= OFF

## **DURABLE**

Waterproof, Dustproof,

Shockproof,

IP68 Rated

# **REAR LED'S**

- · 1st Press= Constant On
- · 2nd Press= Constant Blinking
- · 3rd Press= Scrolling Sequence
- · 4th Press= OFF
- · Hold= Battery Level Indicator

## **WORK LIGHT**

- · 1st Press= Single LED On
- · 2nd Press= OFF
- Hold= Standard Operating Mode
   (All Front LED's On, Rear LED's Flashing)

GUARDIAN

# BUILT IN MAGNET

Super Strong Built-in Rare Earth Magnet Mounting System (on underside)

# BRIGHTNESS SETTINGS

Max, High, Medium, Low or SOS Light Pattern

## CHARGING PORT

Rechargeable Type-C USB Charging Port

# FRONT LED'S

- · 1st Press= Constant On
- · 2nd Press= Constant Blinking
- · 3rd Press= Scrolling Sequence
- · 4th Press= OFF
- Hold On/Off = All Front LEDS





# Get Going with Your Guardian Angel

### TETHER ATTACHMENT

#### **EMERGENCY MODE**

- · (1) FRONT & REAR FLASHING
- · (2) OFF
- · (3) HOLD: ALL LEDs FLASHING
- (4) DOUBLE PRESS: TURNS OFF ALL LEDs



#### **HOW-TO VIDEOS**



#### **REAR LEDs**

- · (1) CONSTANT ON
- · (2) CONSTANT FLASHING

**TOP FOCUSED** -

· (2) FLASHING

**LED** 

· (1) ON

· (3) OFF

- (3) SCROLLING SEQUENCE MOVES LEFT TO RIGHT - FRONT VIEW
- · (4) OFF
- HOLD: BATTERY LEVEL INDICATOR



#### **WORK LIGHT**

- · (1) RED LED ON
- · (2) RED LEDs ON
- (3) WHITE LEDS ON/RED OFF
- · (4) OFF
- HOLD: STANDARD OPERATING MODE

#### BRIGHTNESS SETTINGS

- · (1) MAX
- · (2) HIGH
- · (3) MEDIUM
- · (4) LOW
- HOLD: ON/ OFF FOR SOS SIGNALING

#### **FRONT LEDs**

- · (1) CONSTANT ON
- (2) CONSTANT FLASHING
- (3) SCROLLING SEQUENCE MOVES LEFT TO RIGHT - FRONT VIEW
- · (4) OFF

#### **ACTIVATE YOUR DEVICE**





**INITIAL USE:** Hold down the front & rear buttons for 2 seconds. The white work light will turn on to signal it's activated. Device will turn on at max brightness.



#### **BRIGHTNESS SETTINGS:**

Push the brightness button until desired setting is reached.

Low/Medium are ideal for most low-light situations.

High/Max are optimal for daytime use. Battery life is shorter on these settings.





**POWERING DOWN:** Hold down the front & rear buttons for 3 seconds to turn it off. The white work light will flash 3 times.

#### PRO TIPS



**PRESS AND HOLD** the small button on the front of the device to activate standard mode. This is the most popular mode, which turns on the white front light and rear flashing lights.



#### **EMERGENCY MODE:**

The big GA button in the middle will activate flashing front and rear lights. Press again to turn it off.



#### QUICK OFF:

Double press the big GA button to turn off all LEDs from any mode.



# ONE LIGHT, DOZENS OF MOUNTS, 1,000s OF USES

Each mount features a built-in rare-Earth magnet (the strongest around) that securely attaches to any Guardian Angel light.

# **MULTI-PURPOSE MOUNTS**



Universal Clip Mount ACC-UCM

Best For: Hats, Belts, Bags, Outer Carrier, Molle Webbing, Radio Strap & Backpacks



Small Universal Clip Mount ACC-UCMS

Best For: Hat Brims, Thin Straps

Jaw Clip Mount ACC-JCM Best For: Quick Detaching, Shirt, Jacket, Backpack, & Safety Vest



Clamp-On Strap Mount ACC-COSM

Best For: Radio Straps, & Straps Up To 1.5" Width



Snap-Lock Mount ACC-SLM Best For: Dog Collars, Leashes & Harnesses



Strap & Epaulet Mount ACC-SCM

Best For: Uniform Epaulets



Arm Strap ACC-MSML

Best For: Walking & Running



Velcro Clip Mount ACC-MVCM

Best For: Any Velcro Surface



Stabilizer Clip Mount ACC-STCM

Best For: Shoulder Mounting

# VEHICLE, EQUIPMENT & GEAR MOUNTS



Cone Mount ACC-MCM Best For: Traffic & Safety Cones



Action Mount ACC-AM Best For: GoPro Action Camera Mounts



Bike/Rail Rubber Strap Mount ACC-RBM

Best For: Handlebars & Rails



Bike/Rail Strap ACC-BSM Best For: Handlebars, Seat Posts, & Bars 0.5"-1.75" Diameter



Velcro Strap Mount ACC-MVSM Best For: Rails, Posts & Vented Bike Helmets



Non-metallic Surface Adhesive & Screw Mount ACC-NMSM

Best For: Any Non-Metallic Surface



Picatinny Rail Mount ACC-MPRM

Best For: Picatinny Rails (Commonly Found On Firearms)



Marine Mount Bundle GRP-M-M-1

Best For: Kayaks, Paddle Sports, Boats, PFDs

# **HELMET MOUNTS**



Hard Hat Earmuff Mount ACC-HHEM Best For: Hard Hats With Earmuff Slots, & Type 2 Safety Helmets



Euro Fire Helmet Mount ACC-FHM Best For: Euro-Style Helmets



Hard Hat Mount ACC-HHM Best For: Hard Hats With Multiple Mounting Locations, & Type I Hard Hats Only



Best For: Traditional Fire Helmet Brims



Helmet Strap With 2 Mounts ACC-HHMS

Best For: Mounting 2 Lights To Helmet



Helmet Rail Mount ACC-MHRM Best For: Tactical Helmets With Mounting Rails